

B0542 | WI 1022D

GB	Powerbank
CZ	Powerbanka
SK	Powerbank
PL	Powerbank
HU	Powerbank
SI	Powerbank
RS HR BA ME	Powerbank
DE	Powerbank
UA	Powerbank
RO MD	Powerbank
LT	Energijos talpykla
LV	Ārējais akumulators
EE	Akupank
BG	Външна батерия
FR	Powerbank
IT	Power bank
ES	Power bank
NL	Powerbank



www.emos.eu

GB | Powerbank

User manual:

Specifications:

Capacity: 10 000 mAh (37.0 Wh)

Accumulator type: Li-Po 3.7 V

Max. input power: DC 5 V/2 A; 9 V/2 A; 12 V/1.5 A – 18 W

Max. output power:

USB-A 1: DC 5 V/3 A; 9 V/2 A; 12 V/1.5 A – 18 W**

USB-A 2: DC 5 V/4.5 A; 9 V/2 A; 12 V/1.5 A – 22.5 W**

USB-C: DC 5 V/3 A; 9 V/2.22 A; 12 V/1.67 A – 20 W**

Max. wireless output power: 15 W

Dimensions: 143 × 70 × 19 mm

Weight: 254 g

Operating temperature: +5 °C ~ 40 °C

Charging time: 4 hours (approximately)*

* *The above charging time may differ depending on ambient conditions.*

* *USB power adapter not included.*

* *Valid when using a USB adapter or power supply providing max. input current (PD 18 W or QC 3.0).*

** *When using both USB outlets at the same time, max. output of the power bank is only 5 V/3 A.*

Instructions for use:

Battery status indicator of the power bank:

- To check the battery status of the power bank, press the button (trapezoid).
- When the button is pressed, the LED display on the opposite side of the power bank displays the current remaining capacity of the power bank expressed in %.

Charging indicator

- While the connected device is charging, % drops and the display is lit.
- During charging, the display is also lit and % increases.

Wireless charging:

- To start wireless charging, first press the button (trapezoid), the icon (wireless) will light up on the display, and then touch the wireless device to the side of the power bank with the magnet.
- If you also discharge the power bank simultaneously when wired charging, the power of both wireless charging and wired charging will be limited to max. 5 V/2 A = 10 W.
- If you charge Apple-branded products, such as the iPhone 12 or 13, wireless charging power is reduced to a maximum of 7.5 W by the Apple device's electronics.
- Unfortunately, this power bank is not compatible with the Apple Watch.
- This power bank cannot be charged wirelessly, only discharged.
- If your phone cover isn't designed for wireless magSafe charging by Apple, we recommend that you remove the cover

when charging wirelessly. This will achieve higher charging efficiency and reduce energy losses during power transfer. To achieve a maximum power of 22.5 W using a green USB port, we suggest use of a suitable USB cable with a throughput of 5 A. The cable that is included in the power bank package has a throughput of only 3 A, so charging may not always work with all smartphone charging platforms at the full speed of 22.5 W

- To extend the battery lifetime, please try to keep its capacity level in the range of 25–75 %.

Supported devices: tablets, mobile phones, cameras, camcorders, MP3 players, GPS navigation, soundboxes.

First charging may take longer than stated.

Carefully read the user manual before use.

It is normal that the cover of the power bank warms up during charging and discharging. It will return to room temperature after the process is complete.

If charging does not begin within 3 seconds, unplug the power bank and plug it in again.

Disconnect all cables after charging. The power bank will turn off automatically.

You can use any of the enclosed cables (if included), or any good quality USB cable to charge and use the power bank.

To achieve the shortest charging time possible, use a USB adapter and cable that can carry current equal or higher than the one stated as input current for the power bank.

The packaging of this product includes a metal ring that is included with the product to ensure better compatibility, speed and stability of wireless charging.

Please always check the charging functionality first before sticking the ring. It is possible that wireless charging of certain mobile phone models may not work optimally with this ring.

You can stick this ring directly on the body of your phone or on the phone cover. Before sticking the ring, first attach it to the MagSafe base of the power bank. Then attach your phone to the powerbank so that charging is successful. This will help you determine where and in what direction to stick the ring.

By using the ring glued to the device you are charging, you will achieve a stronger connection to the magnetic wireless base on the powerbank. For some phone models, you will also achieve greater stability and faster charging speeds (a green lightning bolt icon will light up on the powerbank display when charging wirelessly quickly).

For some phone models, wireless charging with this powerbank only works when using the ring. So if wireless charging doesn't work for you, try using this ring.

Wireless charging is also affected by the use of the phone's protective cover. So if wireless charging doesn't work for you, try it without using this cover.

You can also use this ring if your phone is an Apple phone and is equipped with a MagSafe mechanism.

This power bank can charge selected „Airpod“ models, but without using the metal ring.

Obsah je uzamčen

Dokončete, prosím, proces objednávky.

Následně budete mít přístup k celému dokumentu.



Proč je dokument uzamčen? Nahněvat Vás rozhodně nechceme. Jsou k tomu dva hlavní důvody:

1) Vytvořit a udržovat obsáhlou databázi návodů stojí nejen spoustu úsilí a času, ale i finanční prostředky. Dělali byste to Vy zadarmo? Ne*. Zakoupením této služby obdržíte úplný návod a podpoříte provoz a rozvoj našich stránek. Třeba se Vám to bude ještě někdy hodit.

**) Možná zpočátku ano. Ale vězte, že dotovat to dlouhodobě nelze. A rozhodně na tom nezbohatneme.*

2) Pak jsou tady „roboti“, kteří se přiživují na naší práci a „vysávají“ výsledky našeho úsilí pro svůj prospěch. Tímto krokem se jim to snažíme překazit.

A pokud nemáte zájem, respektujeme to. Urgujte svého prodejce. A když neuspějete, rádi Vás uvidíme!