

AKAI

ALARM CLOCK WITH WIRELESS CHARGER

ACRB-2000

I. Function Buttons



II. Functions

A. Power Connection

1. Plug the USB-A end of cable into the power adapter while plug Type-C end into the product.
2. The product will be ready and stand by after all indicators are on.

B. Wireless Charging

1. Output: 15W
2. Indicator Display:
 - Power connection successful – blue light flashes once
 - Standby – light off
 - Charging – blue light on
 - Charged – light off
 - FOD – blue light flashes continuously

C. Alarm Clock Functions

1. Four Buttons: Alarm, +, -, Light.
2. Time System Setting:

Double click Alarm button to setup 12-hour time and 24-hour time system. PM will display while 12-hour time system is set.
3. Time Setting:
 - 1) Click Alarm button once to enter minute setting, adjust value with +/-;
 - 2) Click Alarm button once after minute setting, to enter hour setting, adjust value with +/-;
 - 3) Click Alarm button a third time to finish time setting.
4. Alarm Setting:
 - 1) Press "+" 3 seconds to activate or deactivate Alarm 1; Press "-" 3 seconds to activate or deactivate Alarm 2. Alarm indicator is on while Alarm is activated;
 - 2) While activated, press Alarm button 3 seconds to enter alarm minute setting, adjust value with +/-;
 - 3) Click Alarm button once after alarm minute setting, to enter alarm hour setting, adjust value with +/-;
 - 4) Click Alarm button a third time to finish alarm time setting;
 - 5) Alarm bell rings 3 minutes before automatic switch-off while no any operation.
 - 6) Touch any button to enter Snooze Mode when bell rings. Bell will ring for 2 more times after 5 minutes. The indicator flashes and Alarm button is out of function during the Snooze Mode. If time setting is needed, please long press "+" to stop alarm 1 or long press "-" to stop alarm 2. All buttons will function normally;
 - 7) Time display brightness can be adjusted manually to 4 grades (Off/Min/Second/Max). "+" and "-" can be used to adjust display brightness manually. The default grade is max brightness when power is connected. Single click "-" to dark the display one grade.
5. Night Light Setting:
 - 1) Night light can be set into 9 color modes: white, RGB shade, red, orange, yellow, green, light blue, blue and pink
 - 2) Touch the Light button once to turn on the night light with white color. Another touch shall allow you to set another color in turn as specified in 5. 1). The last touch will turn off night light.
6. Eco-power function:
 - 1) The battery is for clock back-up only.
 - 2) All functions are out during power disconnection. Functions restored when power is connected.

D. Notes

1. **Attention:** In order to function alarm, wireless charging, night light and USB output all together, power shall be connected by a QC2.0 or QC3.0 adapters. If connected by a 5V adapter, only wireless charging and alarm can work together.

2. Do not squeeze or collide.
3. Do not disassemble or put into the fire, water, to avoid short-circuit leakage.
4. Do not use wireless chargers in severe high temperature, humidity or corrosive environments to avoid leakage of damaged circuits.
5. Do not place too close to magnetic cards (ID cards, bank cards, etc.) with magnetic strips or chips to avoid magnetic card failure.
6. Keep more than 20cm between the implanted medical device (pacemaker, implantable cochlea, etc.) and the wireless charger to avoid potential disruption to medical devices.
7. Keep children from the product in case they play the wireless charger as a toy to avoid accidents.
8. Keep the wireless charger and receiver device away from water and other liquids.
9. To clean the charger, make sure the power supply is disconnected.
10. Usage temperature: 0-45°C.
11. Usage humidity: 20-85% (40°C)
 - ❖ All pictures shown are for illustration purpose only. Actual product may vary due to product enhancement.
 - ❖ Power adapter is not included. Please purchase otherwise or use phone original adapter.

III. Specifications

Input: 5V/3A, 9V/3A, 12V/2A

Output power: 15W (MAX)

Charging efficiency: 75%

Charging distance: ≤8mm

Frequency: 110-205KHz

Size: 140x117x73 mm

IV. Accessories

USB cable (1 meter)

Instruction manual

V. Compatible Devices

Products qualified with Qi standard.

DISPOSAL OF ELECTRICAL AND ELECTRONIC EQUIPMENT



This symbol on the product or packaging means that the product should not be treated as household waste. Do not throw garbage at the end of its life, but take it to a collection center for recycling. In this way you will help to protect the environment and be able to prevent any negative consequences that it would have on the environment and human health. To find your nearest collection center:

- . Contact local authorities
- . Access the website: www.mmediu.ro
- . Request additional information from the store where you purchased the product.

Obsah je uzamčen

Dokončete, prosím, proces objednávky.

Následně budete mít přístup k celému dokumentu.



Proč je dokument uzamčen? Nahněvat Vás rozhodně nechceme. Jsou k tomu dva hlavní důvody:

- 1) Vytvořit a udržovat obsáhlou databázi návodů stojí nejen spoustu úsilí a času, ale i finanční prostředky. Dělali byste to Vy zadarmo? Ne*. Zakoupením této služby obdržíte úplný návod a podpoříte provoz a rozvoj našich stránek. Třeba se Vám to bude ještě někdy hodit.

**) Možná zpočátku ano. Ale vězte, že dotovat to dlouhodobě nelze. A rozhodně na tom nezbohatneme.*

- 2) Pak jsou tady „roboti“, kteří se přiživují na naší práci a „vysávají“ výsledky našeho úsilí pro svůj prospěch. Tímto krokem se jim to snažíme překazit.

A pokud nemáte zájem, respektujeme to. Urgujte svého prodejce. A když neuspějete, rádi Vás uvidíme!